

Product data sheet

Specifications



substation - S60 - Sepam series 60

59787

Main

Relay application	Substation
Range of product	Sepam series 60
Device short name	S60
Control and monitoring type	Circuit breaker/contactors control ANSI code: 94/69 (option) Latching/acknowledgement ANSI code: 86 Logic discrimination ANSI code: 68 (option) Switching of groups of settings Annunciation ANSI code: 30 Automatic transfer (AT) (option) Logic equation editor 200 operators

Metering type	Positive sequence voltage Vd/rotation direction Frequency Calculated active and reactive energy (+/- W.h, +/- VAR.h) Active and reactive energy by pulse counting (+/- W.h, +/- VAR.h) (option) Phase current I1, I2, I3 RMS Demand current I1, I2, I3 Peak demand current IM1, IM2, IM3 Measured residual current I'0 Voltage U21, U32, U13, V1, V2, V3 Residual voltage V0 Negative sequence voltage Vi Active power P, P1, P2, P3 Reactive power Q, Q1, Q2, Q3 Apparent power S, S1, S2, S3 Peak demand power PM, QM Power factor Measured residual current I0, calculated I'0Σ
----------------------	--

Network and machine diagnosis type	Unbalance ratio/negative sequence current li Disturbance recording Tripping context Phase fault and earth fault trip counters Harmonic distortion (THD), current and voltage Ithd, Uthd Difference in amplitude, frequency and phase of voltages with synchro-check option Cable arcing fault detection Phase displacement Datalog (DLG)
---	--

Switchgear diagnosis type	Cumulative breaking current CT/VT supervision ANSI code: 60FL Trip circuit supervision ANSI code: 74 (option) Nb of operations, operating time, charging time, nb of racking out operations (option)
----------------------------------	---

Complementary

Type of measurement	Frequency Current Voltage Peak demand power Energy Power factor Harmonic distortion (I THD & U THD) Power (P,Q)
----------------------------	--

Protection type	Recloser (4 cycles) ANSI code: 79 (option) Neutral voltage displacement ANSI code: 59N
------------------------	---

Breaker failure ANSI code: 50BF
 Synchro-check ANSI code: 25 (option)
 Earth fault/sensitive earth fault ANSI code: 50N/51N
 Earth fault/sensitive earth fault ANSI code: 50G/51G
 Negative sequence/unbalance ANSI code: 46
 Overfrequency ANSI code: 81H
 Underfrequency ANSI code: 81L
 Positive sequence undercurrent ANSI code: 27D
 Remanent undervoltage ANSI code: 27R
 Negative sequence overvoltage ANSI code: 47
 Phase overcurrent ANSI code: 50/51
 Undervoltage (L-L or L-N) ANSI code: 27
 Rate of change of frequency ANSI code: 81R
 Overvoltage (L-L or L-N) ANSI code: 59

Communication port protocol	Measurement readout (option) : Modbus Remote indication and time tagging of events (option) : Modbus Remote control orders (option) : Modbus Remote protection setting (option) : Modbus Transfer of disturbance recording data (option) : Modbus
------------------------------------	---

Input output max capacity	28 inputs + 16 outputs
----------------------------------	------------------------

Communication compatibility	IEC 61850 Modbus TCP/IP Modbus RTU DNP3 IEC 60870-5-103 IEC 61850 gose message
------------------------------------	---

User machine interface type	Without Remote Advanced Mimic-based
------------------------------------	--

Packing Units

Unit Type of Package 1	PCE
-------------------------------	-----

Number of Units in Package 1	1
-------------------------------------	---

Package 1 Height	1.0 cm
-------------------------	--------

Package 1 Width	1.0 cm
------------------------	--------

Package 1 Length	1.01 cm
-------------------------	---------

Package 1 Weight	100.0 g
-------------------------	---------

Recommended replacement(s)